

XP-V320N / V330N

Thermal Receipt Printer

- Wireless port available.
- Wall mount capable.
- Cutter life upgrade to 1.5 million.
- Support cutter auto calibration function.
- Support firmware update online .

Xprinter®



Coffee Shop



Shopping




Mart



Wall-hanging

XP-V320N/V330N

Thermal Receipt Printer



Model	XP-V320N		XP-V330N	
Printing method	Direct thermal			
Paper width	79.5±0.5mm			
Print width	72mm/ 76mm/ 80mm/ 64mm/ 48mm/ 52mm			
Column capacity	576 dots/line			
Printing speed	200 mm/s Max.		260 mm/s Max.	
Interface	USB+Lan / USB+Serial(Optional:Bluetooth/WIFI)		USB+Serial+Lan	
Line spacing	3.75mm （Adjustable by commands）			
Column number	80mm paper: Font A - 42 columns or 48 columns/Font B - 56 columns or 64 columns/ Chinese, traditional Chinese - 21 columns or 24 columns			
Character size	ANK, Font A: 1.5×3.0mm (12×24 dots) Font B: 1.1×2.1mm (9×17 dots) Chinese, traditional Chinese:3.0×3.0mm (24×24 dots)			
Cutter				
Auto cutter	Partial			
Barcode Character				
Extension character sheet	PC347(Standard Europe) / Katakana / PC850(Multilingual) / PC860(Portuguese) / PC863(Canadian-French) / PC865(Nordic) / West Europe / Greek / Hebrew / East Europe / Iran/WPC1252 / PC866(Cyrillic#2) / PC852(Latin2) / Pc858 / IranII / Latvian / Arabic / PT151(1251)			
Barcode types	UPC-A/UPC-E/JAN13(EAN13)/JAN8(EAN8)/CODE39/ITF/CODABAR/CODE93/CODE128			
2D Barcode	QR CODE / PDF417 (Available in USB+Lan)		QR CODE / PDF417(Available in USB+Serial+Lan)	
Input buffer	64 Kbytes / 128 Kbytes			
NVFlash	256 Kbytes			
Power				
Power adaptor	Input: AC 100-240V/50~60Hz; Output: DC 24V/2.5A			
Printer input	DC 24V/2.5A			
Cash drawer	DC 24V/1A			
Physical characteristics				
Weight	1.0 Kg			
Dimensions	184 ×140×142 mm (D×W×H)			
Environmental Requirements				
Operation environment	Temperature (0 ~ 45℃) humidity(10 ~ 80%)			
Storage environment	Temperature(-10 ~ 60℃) humidity(10 ~ 90%)			
Reliability				
Cutter life	1.5 million cuts			
Printer head life	150 KM			
Software				
Emulation	ESC/POS			
Driver	Windows/JPOS/ OPOS/Linux/Android/Mac			
Utility	Windows & Linux test Utility			
SDK	iOS/Android/Windows			



Scan QR code to checkout Xprinter website for more update information.
Phone: (+86 756) 3895 852
Http://www.xprintertech.com
Email: overseas@xprinter.net

